


1. Name and Parts



- 1. 2MP Digital Lens
- 2. Microphone
- 3. Locking Connector

* No microphones are available for USA market.

2. Package Content



Full HD Digital Handbag Camera



Quick Guide


※ Do not remove serial number sticker!
Warranty is invalid if the sticker is tampered.

1

3. Connect Handbag Covert Camera to DVR

1. To connect the camera, fully plug the camera's connector end into the **Camera In** port on the DVR, then lock the connector firmly by rotating it to the direction of the red arrow.


- ※ Only connect the camera to DVR when system is turned off.
- ※ Make sure both camera and memory card are inserted into DVR before turning the system on.



LawMate Portable DVR
(Compatible with PV-500Neo & PV-500Neo Pro)

2

- 2. Carefully open the velcro hidden pocket following red arrow pointed direction.
- 3. Place the portable DVR underneath the hidden layer and close it.



3


3. Specification

Built in Image Sensor	1/2.9" progressive CMOS Sensor
Sensor Resolution	2000x1121
Pixel Size	2.8um(H) * 2.8um(V)
Digital Picture Resolution	(H)1920x(V)1080
Sensor Sensitivity	0.03 Lux @ F 2.0
Lens F/No.	F2.0
Focal Length	4.3mm
Angle of view	78°
Depth of View	50 cm ~ ∞
Electronic Shutter	1/8 ~ 1/30,000
Video Output	I2C Data
Power Supply Current	220mA
Operating Temperature	-10°C ~ 60°C
Operating Humidity	20 ~ 90%
Storage Temperature	-30°C ~ 80°C
Power Input	DC 3.3V ± 5%
Dimension	28 x 8 x 20 (cm)
Weight	406g

4

HB-18Neo

2MP Full HD Digital
Handbag Design Camera
Quick Guide



LawMate, innovation never stops

LawMate®

V1.0